

## WX-SE200 Expansion Receiver



Designed to be used with Panasonic's WX-SR204 4-channel wireless receiver, the WX-SE200 expansion receiver allows you to add up to 4 additional wireless microphone channels an existing Panasonic 4-channel system without the need to add an additional antenna to the system\*. Choose between Panasonic's WX-ST200 handheld mics and/or WX-ST400 lavalier mic + wireless bodypacks) for microphone options. Perfect for classrooms, conference rooms, auditoriums, museums, or even bars/ restaurants, the WX-SE200 features a RJ45 (CAT5 / CAT5e / CAT6) connection to the Panasonic WX-SR204 4-channel wireless receiver, and secure Euroblock connectors for independent channel outputs, external audio input and a mix output. LEDs on the front panel show the system status during startup & microphone pairing, antenna status during operation, and an LED indicator of when the receiver is being controlled remotely. Ships with rack ears for easy rack mount installation.

*\*Depends on room side and desired coverage.*



### Key Features:

- Expansion to up to 4 additional wireless mic channels to an existing 4-channel system (WX-SR204 required) without the need to install additional antennas. \*
- Easy to setup – no need for planning / allocation of channels; Secure pairing with Panasonic microphones
- Supports external audio input and mixing with mic channels
- Rack mountable (1u high, rack ears included)

## WX-SE200 Specifications

<b>Channel Output Circuits:</b>	4
<b>Channel Output Connectors:</b>	Euroblock
<b>Channel Output Characteristics:</b>	-10dBV balanced 600 Ohms
<b>Channel Output Signal to Noise Ratio:</b>	70 dB or greater
<b>Channel Output Frequency Response:</b>	50 Hz to 15 kHz
<b>Channel Output Distortion:</b>	<3%
<b>Audio Input Characteristics:</b>	-10 dBV balanced 600 Ohms
<b>Audio Input Frequency Response:</b>	50 Hz to 15 kHz
<b>Audio Input Distortion:</b>	<3%
<b>Mix Output Connectors:</b>	Euroblock
<b>Mix Output Characteristics:</b>	-10 dBV Balanced 600 Ohms
<b>Mix Output Signal to Noise Ratio:</b>	64 dB or greater
<b>Mix Output Frequency Response:</b>	50 Hz to 15 kHz
<b>Mix Output Distortion:</b>	<3%
<b>Extension Connector</b>	1 x RJ45, for WX-SR202 4-ch Receiver (required; sold separately)
<b>Display Indicators:</b>	Power, Sync, Main, Remote, RF Level (5-level display), Audio level / mute, Mic battery, Register
<b>Power Source / Power Consumption:</b>	AC 120 V 60 Hz / 39 Watts
<b>Operating Ambient Temperature:</b>	32° F to 113°F (0°C to 45°C)
<b>Accessories Included:</b>	Rack Ears
<b>Warranty (Parts &amp; Labor):</b>	3 years
<b>Dimensions (W x H x D):</b>	16-17/32 x 1-47/64 x 9-27/32 inches (420mm x 44mm x 250mm)
<b>Weight (including battery):</b>	6.17 lbs. (2.8 kg)