

## WX-ST400 Lavalier Microphone + Wireless Bodypack

Part of Panasonic's SR200P 1.9 GHz Digital Wireless Microphone system, the WX-ST400 lavalier microphone + wireless bodypack is the perfect solution for education and/or corporate presentations. This condenser microphone is optimized for vocal clarity with Panasonic's proprietary filtering to eliminate noise yet provide clear and original sound quality with a flat frequency response. The wireless bodypack is powered by one AA standard or rechargeable battery and can be placed in the speaker's pocket, on top of a podium or clipped to their belt. The bodypack also features a 3.5mm audio input connector, so the end user can easily use the same system to transmit audio from a local source such as a laptop. Contactless desktop charger (WX-SZ200 or WX-SZ600) sold separately.



### Key Features:

- Crystal Clear Sound, Optimized for Vocal Presentations
- Easy setup, with automatic channel assignment thanks to DECT 1.9 GHz wireless technology
- Lightweight (0.21 lbs. with battery included)
- Rugged and Durable
- Only one AA battery required (alkaline or rechargeable)
- Easy & Convenience to use

Leveraging Panasonic's 20-year experience in DECT wireless audio communications, the WX-SR200P 1.9 GHz digital wireless microphone system is the best-in-class solution for classroom or corporate presentations providing low latency for hybrid in-room/virtual presentations. Panasonic's digital wireless microphone system is easy to set up, easy to integrate with third-party control systems (such as Crestron, Extron, and Q-SYS) and easy to use. Setup is a breeze - the wireless microphones pair wirelessly with Panasonic's digital wireless mic receiver and assigns channels automatically, eliminating the need for manual channel assignment. The system can be expandable to suit a variety of spaces, from small classrooms, medium sized classrooms / conference rooms, to large auditoriums. Up to 8 separate antennas (per receiver) can be mounted to the wall or the ceiling in the room and connected via CAT5 back to the receiver locked away in a cabinet or closet and multiple digital wireless microphone receivers can be installed to add wireless microphone channels to the room

## WX-ST400 Specifications

<b>Microphone Element:</b>	Electret Condenser
<b>Microphone Polar Pattern:</b>	Cardioid
<b>Microphone Frequency Response:</b>	100 Hz to 15 kHz
<b>Microphone Input:</b>	2.5mm jack (two contacts) (1) Signal (Bia DC 2.5 V) (2) GND
<b>Line Input:</b>	3.5mm jack (three contact for Monaural Mixing) (1) Stereo L (2) Stereo R (3) GND
<b>Wireless Frequency:</b>	1920 MHz to 1930 MHz
<b>Operating Ambient Temp.:</b>	41° F to 95° F (5° C to 35°C)
<b>LED Indicators:</b>	Power, Charge
<b>Battery Required:</b>	Rechargeable: 1 x AA Ni-MH Dry cell: 1 x AA alkaline
<b>Battery Life:</b>	NI-MH: Approx. 8 hours Alkaline: approx. 6 hours
<b>Warranty (Parts &amp; Labor):</b>	3 years
<b>Bodypack Dimensions (W x H x D):</b>	2-23/64 x 3-13/16 x 25/32 inches (60mm x 97mm x 20mm)
<b>Lavalier Mic Dimensions (Max. Diameter x L)</b>	33/64 x 55/64 inches (13 mm x 22mm)
<b>Bodypack Weight (including battery):</b>	0.21 lbs. (95 g)